

**C-212ii**

Woofer	filter type	Order	Gain	Freq	Q
	High Pass	2	0	50	0.8
	High Pass	2	0	50	0.8
	Low Pass	2	0	500	0.707
	Low Pass	2	0	500	0.707
	Parametric EQ	2	-15.8	1625	3.7
	Parametric EQ	2	-27	3650	4.1
	Parametric EQ	2	2.2	351	3.6
	Parametric EQ	2	3	300	5
	Parametric EQ	2	-1.5	140	5

  

Midrange	filter type	Order	Gain	Freq	Q
	High Pass	2	0	500	0.7071
	High Pass	2	0	500	0.7071
	Low Pass	2	0	2200	0.7071
	Low Pass	2	0	2200	0.7071
	Parametric EQ	2	-20	60	7
	Parametric EQ	2	-5.5	368	5
	Parametric EQ	2	-7.5	300	4
	Parametric EQ	2	-8.08	2489.81	6.7906
	Parametric EQ	2	-5	1480	6
	Parametric EQ	2	-10	3021	4
	Parametric EQ	2	3	508	7
	Parametric EQ	2	-1.5	600	8
	Parametric EQ	2	-3	1210	10

  

Horn	filter type	Order	Gain	Freq	Q
	High Pass	2	0.5	2200	0.7071
	High Pass	2	0.5	2200	0.7071
	Parametric EQ	2	-9.75	4832	1.2
	Parametric EQ	2	2.3	6444	3.7
	Parametric EQ	2	2.5	14384	3.7
	Parametric EQ	2	-3.5	3108	4
	Parametric EQ	2	-14	515	3
	Parametric EQ	2	-4.5	4618	4.1
	Parametric EQ	2	-16	775	5
	Parametric EQ	2	3.5	13335	5.6
	Parametric EQ	2	-3.5	8212	3.6
	Parametric EQ	2	-4	11000	12
	Parametric EQ	2	-1	1850	11
	Parametric EQ	2	2	2200	12

**C-212ii**

<b>limiter</b>	average (ms)	attack (ms)	Decay (ms)	Threshold	ratio
LF	33	0.005	200	-5	30:1
MF	10	0.005	200	-6	30:1
HF	2	0.005	200	-8	30:1
<b>Delay</b>	LF 0.14 ms	MF 0.14 ms	HF 0		
<b>Polarity</b>	LF normal	MF normal	HF Reversed		