

C-212X-1150 DSP settings

Woofers (chan 1 & 4)

filter type	Order	Gain	Freq
High Pass	2	0	45
High Pass	2	0	45
Low Pass	2	0	1500
Low Pass	2	0	1500
Parametric EQ	2	-5.5	600
Parametric EQ	2	-4.5	1600
Parametric EQ	2	-4	435

Horn (chan 6)

filter type	Order	Gain	Freq
High Pass	2	1	1500
High Pass	2	1	1500
Parametric EQ	2	-8.5	3130
Parametric EQ	2	2	7617
Parametric EQ	2	-3	13128
Parametric EQ	2	-4	1800
Parametric EQ	2	-2.8	3532
Parametric EQ	2	-19	580
Parametric EQ	2	-6.5	1150
Parametric EQ	2	2	9926
Parametric EQ	2	2.5	5931
Parametric EQ	2	-17	350

C-212X-1150

limiter	average (ms)	attack (ms)	Decay (ms)	Threshold
LF	28	0.1	200	-5
MF	28	0.1	200	-5
HF	5	0.001	200	-10
Delay	LF	MF	HF	
	0	0	0	
Polarity	LF	MF	HF	
	normal	normal	Reversed	

Q

0.6

0.6

0.707

0.707

4.5

4

8

Q

0.7071

0.7071

2.6

2.6

10

5

3.7

4

4

5.6

6.8

5

ratio

30:1

30:1

30:1