

Tvi Audio C-210ii-552 DSP settings

Channel

Channel	Filter	slope	Gain	frequency	Q
LF1 & LF2 (chan 1 & 4)	High Pass	2	0	50	1
	High Pass	2	0	50	1
	Low Pass	2	0	1500	0.707
	Low Pass	2	0	1500	0.707
	Parametric EQ	2	-3.5	644.77	0.7071
	Parametric EQ	2	-3	380	4.7
	Parametric EQ	2	-2.36	786.7	5.3
	Parametric EQ	2	-2.5	1500	8

Channel	Filter	slope	Gain	frequency	Q
HF (chan 6)	High Pass	2	0	1500	0.7071
	High Pass	2	0	1500	0.7071
	Parametric EQ	2	-10	3022.07	1.7
	Parametric EQ	2	-5.55	1117.6	3.5
	Parametric EQ	2	2.26	12748.64	2.5
	Parametric EQ	2	-3	1850	5.3
	Parametric EQ	2	-2	5500	5
	Parametric EQ	2	-9.98	682.13	2.8
	Parametric EQ	2	-3.5	1250	4.2
	Parametric EQ	2	-2.5	3400	8
	Parametric EQ	2	2	2700	8

limiter	average (ms)	attack (ms)	Decay (ms)	Threshold	ratio
LF1 & LF2	28	0.1	200	-5	30:1
HF	2	0.1	200	-10	30:1

Delay	LF1 & LF2	HF
	0.2 ms	0

Polarity	LF1 & LF2	HF
	normal	Reversed